AlphaGen[™] Portable 3.0kW Portable 36/48Vdc Generator System



Your Power Solutions Partner

- > Compact portable generator lets you deploy power when/where you need it
- > DC technology requires no UATS (Universal Automatic Transfer Switch)
- > No need to disconnect or reconnect power supply to utility power
- Selectable output for 36 or 48Vdc operation up to 3000W
- Quiet operation only 58dBA @ 7m (22ft)
- > Completely enclosed, water resistant for safe operation in the field
- > Oversized metal gas tank with level gauge for extended runtimes of up to 20hrs

Alpha expands its generator family to include a portable 3.0kW DC generator. The compact, lightweight AlphaGen generator is designed specifically for powering cable television, telecommunications and broadband applications that do not have integrated generators as a primary component of the power system.

The portable generator incorporates several technological advantages including: 36 or 48V selectable dual voltage output based on Permanent Magnet Generator (PMG) technology, 3000W of power and oversized fuel tank for up to 20hrs of runtime at 25% load or 7.2hrs at 100% load.

Additional features include a convenient front panel with a keyed on/off switch, output connector, output indicators, voltmeter, fuel valve and engine choke.





AlphaGen™ Portable 3.0kW Portable 36/48Vdc Generator System

P/N: 013-018-10-010

PERFORMANCE / FEATURES

single cylinder, manual recoil starting,

manual choke

Rated power:2800W continuous, 3000W max

Alternator:Permanent magnet, brushless, bearingless

Dual range selector:

Output regulation:.....1Vdc

Control features: Automatic voltage regulation

Electronic governor Over current protection

Analog voltmeter with back light **Cable interface:**.....Anderson type SBE-80 connector

Runtime:

Audible noise:Approx. 58dBA @ 7m under full load

Frame:Fully enclosed

MECHANICAL

Dimensions:

AGENCY COMPLIANCE

CSA C22.2 No. 100-95, 107.1-01,107.2-M89, 0.4 FCC part 15B Class A

REQUIRED ACCESSORIES

Output interface cable:Available in 10', 30' or 50' lengths Battery interface cable:Choose ring lung, heavy-duty alligator clamp, or Y-adapter*

*Connects the power supply's battery input directly to the generator



30' Output interface 10' P/N 877-567-10-022 50' P/N 877-567-10-021



Ring lug battery interface



Alligator clamp battery interface P/N 874-946-20




Y-Adaptor battery P/N 874-946-22

Optional accessories:


DCX-PG-WK:	Portable generator wheel kit
AG-PG-TOOL:	Punch tool kit for enclosures
AG-PG-UK:	Enclosure upgrade kit
DCX-PG-HANDLE:	Locking handle
AG-CAB-KIT	Cable bag with cable and key lanyard

3.0KW PORTABLE GENERATOR SOUND LEVELS

Ambient background noise level at 45dBA All readings are 8 point averages



Generator at 100% rated load



Generator at 100% rated load (typical)



AlphaGen front view



AlphaGen portable trailer



AlphaGen with wheel kit

Alpha Technologies Ltd.

For more information visit www.alpha.ca

 Canada: Burnaby, British Columbia
 T: 604.436.5900
 F: 604.436.1233

 United States: Bellingham, Washington
 T: 360.647.2360
 F: 360.671.4936

#0470049-00 Rev B (07/2016)